



Arab Academy for Science & Technology and Maritime Transport

College of Engineering and Technology

Department : Electronics and Communications

Course : Electronic Measurements (Mech.)

Course Code: EC416

Lecturer : Prof. Dr. Ashraf Mamdouh

GTA : Eng. Sherry Heshmet

Problem Set #1

Cathode-Ray Oscilloscopes

- 1-** A 500 Hz triangular wave with a peak amplitude of 40 V is applied to the vertical deflecting plates of a CRT. A 250 Hz sawtooth wave with peak amplitude of 50 V is applied to the horizontal deflecting plates. The CRT has a vertical deflection sensitivity of 0.1 cm/V and a horizontal deflection sensitivity of 0.08 cm/V. Assuming that the two inputs are synchronized, determine the waveform displayed on the screen.

- 2-** A 1 kHz triangular wave with peak amplitude of 10 V is applied to the vertical deflecting plates of a CRT. A 1 kHz sawtooth wave with peak amplitude of 20 V is applied to the horizontal deflecting plates. The CRT has a vertical deflection sensitivity of 0.4 cm/V and a horizontal deflection sensitivity of 0.25 cm/V. Assuming that the two inputs are synchronized. Determine the waveform displayed on the screen.

- 3-** Repeat **problem 2** with the triangular wave frequency changed to 2 kHz.