



**Arab Academy for Science & Technology
and Maritime Transport – Cairo Branch
College of Engineering & technology
Electronics & Communication Engineering Department**



EC443 EM Transmitting Media

**Instructor: Prof. Esmat Abdel Fattah
Tutorial : Eng. Sherif Eldyasti**

Problems Set #8

Cavity Resonators

1. A section of 1.5 in* 3 in is air-filled wave guide which is 4 in long and is shorted at each end, forming a cavity. Find the three lowest resonance frequencies.
2. an air-filled rectangular cavity resonator has dimensions of $a=5$ cm, $b=2$ cm, $d=15$ cm. compute:
 - a- the resonant frequency and the corresponding mode.
 - b- The frequency range between the lowest resonant frequency and the following resonant frequency.
 - c- Repeat a and b for $d=5$ cm.
 - d- Repeat a and b if the dielectric constant equals 2.
3. calculate the Q-factor for a copper resonator having $a=2.286$ cm and $b=1.016$ cm and $d=4.5$ cm. given that it is resonating at the TE₁₀₁ mode
4. A rectangular cavity having $a=2$ cm and $b=1$ cm and $d=6$ cm. it is filled with a dielectric having permittivity $2.5-j0.0001$ at the resonant frequency of the TE₁₀₁ mode. The cavity is made of copper. Find the Q-factor for the TE₁₀₁ mode.
5. An air-filled circular wave guide with a radius of 3 cm operating at the TE₀₁₁ mode at 10 Ghz by placing two conducting plates at its two ends. Determine the minimum distance between them.

Good Luck ☺