

Sheet 1: Analog Input/Output

1- Read the data in the input analogue port (x) and output the analogue value(y):

a) $Y = \frac{x}{3} + 5$

b) $Y = \frac{32000}{x} * 5 - 2.5$

c) $Y = \frac{1}{N} \sum_{i=1}^N x(i) * T$ where T=10msec, N=4 and x(i) is the value of input x at instant i

d) $Y = \frac{x(i)-x(i-1)}{T}$

2- Read the data in the input analogue port (x) and scale it to:

a) 100 to 1000 °C

3- Write a program to read the analogue (x) and analogue input (y) and output analogue value (u):

$$e_i = x_i - y_i, e_{i-1} = x_{i-1} - y_{i-1}, e_{i-2} = x_{i-2} - y_{i-2}$$

$$u_i = u_{i-1} + k_p(e_i - e_{i-1}) + \frac{k_d}{T}(e_i - 2e_{i-1} + e_{i-2}) + \frac{k_i}{N}e_iT$$

4- Find the minimum value and maximum value of u_i in (3).

5- Read the data in the input analogue port (x) for three values and find:

a) Average

b) Min and Maximum value

c) Root mean

$$\sigma = \sqrt{\frac{1}{N} \sum x_i^2}$$

6- A process consists of a pressure sensor with an output voltage of 1V/psi.

Three indicators are used in the process:

a) Normal operation (<5 Psi)

b) Warning condition (>5 Psi & < 7 Psi)

c) Alarm condition (>7Psi).

Draw a ladder diagram for measuring the pressure and operating the three indicators.

7- A heating tank consists of a temperature and pressure sensor with an output voltage of $0.01V/^{\circ}C$ and $0.1V/pal$. The process operates operate as follows:

- a) If $P < 3pa$ and $T < 10^{\circ}C$ → Heater on
- b) If $P > 3pa$ and $T > 50^{\circ}C$ → Heater off
- c) If $P > 5pa$ and $T < 50^{\circ}C$ → Safety valve open
- d) If $P > 5pa$ and $T > 50^{\circ}C$ → Alarm indicator flash

Draw a ladder diagram for operating the process